

Wouxun KG-UV8D Frequency Programming

#1: set VFO/MEM to Frequency mode

#2: Enter frequency via keypad, press Menu

#3: Select menu #16: Press Menu, select/enter PL code (i.e. 136.5), press Menu to register change.

#4: Select menu #23: Press Menu, select/enter offset (usually .600 KHz for 2m / 5.0 MHz for 70CM). Press Menu to register change.

#5: Select menu #24: Press Menu to select/enter +/- /off Shift (Simplex uses OFF). Press Menu to register change.

#6: Select menu #27: Press Menu to enter memory channel location (black means used, Blue means vacant). Press Menu & THEN Exit to register change.

#7: Press Menu: Select menu #26: Press Menu to change channel name. Press Menu to register change, & press Exit to finalize.

I hope this helps your HT radio experience. Ham operators, send comments to me via ARRL email.

73

Craig - KC1ELZ